

## TC-446S

### Professional License-free Radio







- License-free Radio
- Light Weight and Tough Design
- Longer Battery Life
- Enhanced Voice Quality



As a combination of cutting-edge analog technologies and usercentered design, TC-446S gives an edge to your productivity and management efficiency. With its compact design and lightweight chassis, this tough radio is an ideal choice for management in facilities, hospitality, manufacturing, retail, education and construction. Besides, TC-446S provides up to 24 hours of battery life to ensure long-lasting performance and convenience. Affordable price and distinct performance - TC-446S deserves your trust.

# TC-446S

#### Professional License-free Radio

#### **Product Features**

#### License-free Radio

With TC-446S, you can enjoy charge-free communication easily.

#### Light Weight and Tough Design

TC-446S has a light-weight but exceptionally strong body, allowing it to be carried about easily and to survive harsh conditions.

#### Longer Battery Life

TC-446S is equipped with a 1650mAh battery that enables you to transmit and receive, on a 5-5-90 basis, for up to 24 hours.

#### **Enhanced Voice Quality**

TC-446S employs advanced voice technologies to better the sound quality during your communication.

#### Applications

- Facilities
- Hospitality
- Manufacturing
- Retail
- Education
- Construction

### Main Features

Voice-operated Transmit (VOX)

Battery Strength Indicator

CTCSS/CDCSS and Squelch Tail Elimination

Busy Channel Lockout

Time-out Timer (TOT)

PC Programmable

Wired Clone

Two Squelch Levels Selectable







#### Accessories

| Standard    | Li-lon Battery (1650mAh) BL1719 | Rapid-rate Charger ( | for Li-lon Battery) CH10L12 |
|-------------|---------------------------------|----------------------|-----------------------------|
| Accessories | Switching Power PS1018          | Belt Clip BC12       | Strap RO03                  |










Earbud with on-MIC PTT & VOX ESM12



t with in-Lir VOX EHM15



(for use with remote sp microphone) ESS0

Programming Cable (COM Port) PC19 Programming Cable (USB to Serial Port) PC26





EAM12

oning C CP05

#### Applicable MIL-STD-810C/D/E/F

| Applicable       | 810C        | 810D      | 810E      | 810F               |
|------------------|-------------|-----------|-----------|--------------------|
| MIL-STD          |             |           |           | Methods Procedures |
| Low Pressure     | 500.1 1     | 500.2 1,2 | 500.3 1,2 | 500.4 1            |
| High Temperature | 501.1 1,2   |           |           | 501.4 1,2          |
| Low Temperature  | 502.1 1     | 502.2 1,2 | 502.3 1,2 | 502.4 1,2          |
| Temp. Shock      |             |           |           | 503.4 1            |
| Solar Radiation  | 505.1 1     | 505.2 1   | 505.3 1   | 505.4 1,2          |
| Rain             |             |           |           | 506.4 1,2          |
| Humidity         | 507.1 2     | 507.2 2,3 | 507.3 2,3 | 507.4 1            |
| Salt Fog         |             |           |           | 509.4 1            |
| Dust             | 510.1 1     | 510.2 1   | 510.3 1   | 510.4 1            |
| Vibration        | 514.2 8,10  | 514.3 1   | 514.4 1   | 514.5 1            |
| Shock            | 516.2 1,2,5 | 516.3 1,4 | 516.4 1,4 | 516.5 1,4          |

| General |
|---------|
|---------|

| Frequency Range(MHz)                                                    | 446.00625 MHz-446.09375 MHz |
|-------------------------------------------------------------------------|-----------------------------|
| Channel Capacity                                                        | 16                          |
| Channel Spacing(KHz)                                                    | 12.5KHz                     |
| Operating Voltage(v)                                                    | 7.4V                        |
| Standard Battery                                                        | 1650mAh (Li-Ion)            |
| Battery Life (5-5-90 Duty Cycle)                                        | Up to 24 hours              |
| Frequency Stability(ppm)                                                | ±2.5 ppm                    |
| Operating Temperature(°C)                                               | -25℃ ~ +60℃                 |
| Antenna Impedance(9)                                                    | 50 Ω                        |
| Dimensions (H $\times$ W $\times$ D)(with battery, without antenna)(mm) | 113x54x35mm                 |
| Weight (with antenna & battery)(g)                                      | 270g                        |

#### Transmitter

|                  | 0.5W    |
|------------------|---------|
| Modulation       | 8K⊕F3E  |
|                  |         |
| FM Noise         | ≤ -38dB |
| Audio Distortion |         |

Receiver

| Sensitivity                 |                                   |
|-----------------------------|-----------------------------------|
| Selectivity                 | ≥60dB                             |
| Intermodulation             |                                   |
| Spurious Response Rejection | ≥70dB                             |
| S/N                         |                                   |
| Rated Audio Power Output    | 800mW (Speaker impedance: 16 ohm) |
| Rated Audio Distortion      | ≤5% (800mW)                       |

All Specifications are tested according to ETSI EN 300 296, and subject to change without notice due to continuous development.



#### Hytera Communications Corporation Limited

Address: Hytera Tower, Hi-Tech Industrial Park North, Beihuan Rd., Nanshan District, Shenzhen, China Tel: +86-755-2697 2999 Fax: +86-755-8613 7139 Post: 518057

#### Http://www.hytera.com

Hytera retains right to change the product design and specification. Should any printing mistake occur, Hytera doesn't bear relevant responsibility. Little difference between real product and product indicated by printing materials will occur by printing reason.

HYT, Hytera are registered trademarks of Hytera Co., Ltd. © 2014 Hytera Co., Ltd. All Rights Reserved.

| Your Local Dealer |  |
|-------------------|--|
|                   |  |
|                   |  |
| 1                 |  |
|                   |  |
|                   |  |
|                   |  |
|                   |  |
|                   |  |
|                   |  |
|                   |  |
|                   |  |
|                   |  |
|                   |  |
|                   |  |
|                   |  |
|                   |  |
|                   |  |
|                   |  |
| 1                 |  |
|                   |  |
|                   |  |
|                   |  |
|                   |  |
|                   |  |
|                   |  |
|                   |  |
|                   |  |
|                   |  |